

All Specifications

Projection System

STAY IN THE KNOW
Projection System

DLP

DMD size

0.23” Pico

Marketing

Main Marketing Series

Portable Projector

Product Features

1. 720P, 300 ANSI lumen 2. 135 degrees projection angle 3. Auto focus 4. Auto vertical keystone ± 40 degrees 5. 2.1 CH sound chamber speakers(4Wx2 +8W woofer) 6. Android TV inside 7. Wireless projection for mutiple OS and devices(Android phone/Chrome browser/iOS devices) 8. Bluetooth speaker mode 9. Drop proof from 70cm(27.6 inch) height 10. USB-C charging, DisplayPort and reader 11. BenQ smart control App for mobile devices 12.2.5 hours battery life

Display

Native Resolution

720p (1280x720)

Native Aspect Ratio

16:9

Brightness (ANSI lumens)

300

Contrast Ratio (FOFO)

100,000:1

Selectable Aspect Ratio

16:9

Display Color

24-bit (16.7 million colors)

Light Source

LED

Light Source Life


a. Normal 20000 hrs,b. ECO 30000 hrs

Optical

Throw Ratio 1.2

Zoom Ratio Fixed

TOP



Buy Now

- LensFixed
- Projection Offset (Full-Height) 100%
- Keystone Adjustment 1D, (Auto) Vertical ± 40 degrees
- ANSI Uniformity (Min.) -35%
- STAY IN THE KNOW
- Clear Image Size 30"~100"
- Image Size 30"~100"

Picture

- Picture Modes Bright,Cinema,Day Time,Game,Living Room,Sports
- Rec. 709 Coverage 98%


Compatibility

- Input Lag 51 ms (1080p@60Hz)
- Resolution Support VGA (640 x 480) to 4K UHD (3840 x 2160),VGA(640 x 480) to Full HD(1920 x 1080)
- HDTV Compatibility 1080i,1080p,2160p,480i,480p,576i,576p,720p
- Video Compatibility EDTV,HDTV,NTSC,PAL,SDTV, SECAM

/O Interface

- HDMI in (x2),HDMI-I (1.4b/HDCPI.4),HDMI-Internal (1.4b/HDCPI.4)
- USB Type C (x1),DisplayPort / PD(only support 45W input)

TOP



[Buy Now](#)

Audio

Speaker (x2),4W

Woofer 8W Chamber

Audio out (3.5mm Mini Jack) (x1)

 Audio EQ Yes

Environment

Power SupplyAC 100 to 240 V, 50/60 Hz

Typical Power Consumption (110V) 65W@100 ~ 240VAC

Acoustic Noise (Typ./Eco.)(dB) 29dBA/27dBA

STAY IN THE KNOW

Operating Temperature 0~40°C

Accessories

Android TV dongle QS01

Carry Bag Yes

Remote Control w/ Battery RCI067

Power Cord (by region) x1 (1.8M) Quick Start Guide (x1)


IL

Installation Guide Yes

Warranty Card (by region) Yes

Battery (Standard)

TOP



[Buy Now](#)

OSD

English 简体中文 Deutsch Español Français

OSD Language Italiano Português Русский 繁體中文 日本語

한국어 ไทย Indonesian

Launcher Smart Home

Smart System

Built-in OS Yes, Android 9.0

ROM/RAM 16GB/2GB

Bluetooth Yes, Bluetooth 4.2

Wi-Fi Standard 802.11 a/b/g/n/ac (2.4G/5G)

Dimension & Weight

Dimensions (WxHxD) (mm) 120.0mm(W)*195.8mm(H)*185.0mm(D)

Dimensions (WxHxD) (inch) 4.7 inch(W)*7.7 inch(H)*7.3 inch(D)

Net Weight (kg) 1.6 kg

Net Weight (lb) 3.53 lb

* The performance of WLAN and Bluetooth might be disturbed by distance and obstacles.

STAY IN THE KNOW

* LED life results will vary depending on environmental conditions and usage. The actual product's features and specifications are subject to change without notice.

* The Contrast is measure by Full On Full Off standard.

Follow Us

[Subscribe Epaper](#)

TOP



Buy Now

example@benq.com

Sub

(https://www.facebook.com/BenQincorporate/https://www.youtube.com/channel/UCBhmtetenprQsic:AA/wmwerwic.yao/utub/het.ctposm:///bwewnqwn.loinrktheadmine.croicma)/company/benq-america)

We Gladly Accept



About BenQ

- Corporate Introduction (https://www.benq.com/en-us/about-benq/corporate.html)
- Corporate Social Responsibility (https://www.benq.com/en-us/about-benq/csr.html)
- News (https://www.benq.com/en-us/news.html)
- Careers (https://workforcenow.adp.com/mascsr/default/mdf/recruitment/recruitment.html?cid=ba6fce2c-8ad846ad-8bfl-093d7fe49c04&cclId=19000101_000001&type=MP&lang=en_US)
- Join Our Email List (https://info.benq.us/benq-america-email-sign-up-form?_hstc=132696849.99d9b60cebcd48a67a27aef1fdd057a1.1632336236227.1633553832153.1633615209300.7&_hssc=132696849.28.1633615209300&_hsfp=4285443617)

Support

- Contact Us (https://www.benq.com/en-us/support/contact-us.html)
- Download & FAQ (https://www.benq.com/en-us/support/downloads-faq.html)

